


Data Sheet

Power Supply 24 V DC (HDXXX24)

<div>HDN1524 HDR1524 HDN2424 HDR3024 HDN6024 HDR6024 HDN9024 HDR10024 HDR10024N</div> <div></div>	<div>Features</div> <ul style="list-style-type: none">• 24 V power supply• DIN-rail mounting• UVP (under-voltage protection), OCP (over current protection), SCP (short circuit protection) and OVP (over-voltage protection)• 3 years warranty• Customization of OEM is welcomed
---	---

Specification

Redisage PN		HDN1524	HDN2424	HDN6024	HDN9024
Output	Rated voltage	24 V			
	Rated current	0.63 A	1 A	2.5 A	3.83 A
	Rated power	15 W	24 W	60 W	90 W
	Adjustment range	23-25 V	22.8-25.2 V		23-25 V
	Ripple	150 mVp-p			
	Type	CV (constant voltage)			
	Efficiency	> 85%	> 79%	> 88%	> 89%
	Protection	OCP, SCP, OVP			
Input	Voltage range	100-240 VAC			
	Frequency range	47-53 kHz			

Redisage PN		HDN1524	HDN2424	HDN6024	HDN9024
No load power consumption	0.25 W		0.35 W		
Protection	OVP, UVP				
Temperatures		0°C to +40°C			
Mounting and enclosure		DIN rail, 1M	DIN rail, 2M	DIN rail, 3M	DIN rail, 4M

Redisage PN		HDR1524	HDR3024	HDR6024	HDR10024	HDR10024N
Output	Rated voltage	24 V				
	Rated current	0.63 A	1.5 A	2.5 A	3.83 A	4.2 A
	Rated power	15 W	36 W	60 W	92 W	100.8 W
	Adjustment range	21.6-29 V				
	Ripple	150 mVp-p				
	Type	CV (constant voltage)				
	Efficiency	86%	89%	90%		
	Protection	OCP, SCP, OVP				
Input	Voltage range	85-264 VAC / 120-370 VDC				
	Frequency range	47-63 kHz				
	No load power consumption	< 0.3 W				
	Protection	OVP, UVP				
Temperatures		-30°C to +70°C				
Mounting and enclosure		DIN rail, 1M	DIN rail, 2M	DIN rail, 3M	DIN rail, 4M	

Additional notes

Related information and links		
Ordering information	Accessories	Similar products

Products family sample photo



<https://redisage.com>

DISCLAMER NOTES

ALL PRODUCT, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE TO IMPROVE RELIABILITY, FUNCTION OR DESIGN OR OTHERWISE.

Datasheet-ID:

SR-D

Revision #9
Created 4 April 2024 13:11:51
Updated 26 July 2024 14:48:32 by Jan Górski